

Cambridge International Examinations

Cambridge International Advanced Subsidiary and Advanced Level

CANDIDATE NAME				
CENTRE NUMBER		CANDIDATE NUMBER		
COMPUTER	SCIENCE		9608/33	
Paper 3 Advanced Theory		October/November 2018		
			1 hour 30 minutes	
Candidates ar	nswer on the Question Paper.			
No Additional	Materials are required.			
No calculators	s allowed.			

READ THESE INSTRUCTIONS FIRST

Write your Centre number, candidate number and name in the spaces at the top of this page.

Write in dark blue or black pen.

You may use an HB pencil for any diagrams, graphs or rough working.

Do not use staples, paper clips, glue or correction fluid.

DO NOT WRITE IN ANY BARCODES.

Answer all questions.

No marks will be awarded for using brand names of software packages or hardware.

At the end of the examination, fasten all your work securely together.

The number of marks is given in brackets [] at the end of each question or part question.

The maximum number of marks is 75.



Question 1 begins on the next page.

1 Consider the following user-defined data type.

TYP	EΒ	ook			
	D	ECLARE	ISBN	:	INTEGER
	D	ECLARE	Author	:	STRING
	D	ECLARE	Title	:	STRING
	D	ECLARE	Supplier		(Amazone, Stones, Smiths, Blackwalls, Greens,
	m	-			Coals, Boarders)
END	TYP.	E			
(a)	Nar	ne the da	ata type of Bo	no l	¢
(4)	itai	110 1110 01	ata typo of Bo	001	Σ.
					[1]
					•
(b)	Nar	ne the no	on-composite	e da	ata type used in the Supplier declaration.
					[1]
	(1)				
(c)	(i)	Write a	pseudocode	sta	atement to declare a variable, BestSeller, of type Book.
					[4]
					[1]
	/ii\	W/rit⊖ s	nseudoco	dρ	statement to assign "John Williams" to the author of
	('')	BestSe	•	uc	statement to assign outin williams to the author of
		200000			

2	(a)	A computer system stores real numbers using floating-point representation. The floating-point
		numbers have:

- eight bits for the mantissa
- four bits for the exponent.

(ii)

(iii)

(b) (i)

The mantissa and exponent are both in two's complement form.

(i) Calculate the denary value of the following floating-point number.

M	lantissa	l				ı	Expo	nent	t			
0 0 1	1 1	0	0	0		0	1	1	1			
Show your work	king.											
Working												
	•••••										•••••	
Angwar												
Answer												3]
State how you k	know the	e floa	ting-	point	t number in part (a	a)(i) i	s no	t norr	nalis	ed.		
											[1	1]
Normalise the fl	loating-p	oint	num	ber i	n part (a)(i).							
M	lantissa	l				ı	Expo	nent	t			
											_	2]
Write the large floating-point nu					that this system	can	repr	esent	t as	a nor	malise)d
M	lantissa	l				E	Expo	nent	t			
					-						[]	21

	(ii)	Write the smallest positive number that can be stored as a normalised floating-poin number in this format.				
		Mantissa	Exponent			
			[2	2		
(c)	The	number of bits available to represent a real number is in				
		e the effect this has on the numbers that can be represe I in the:	nted, if the additional four bits ar	e		
	(i)	mantissa				
			[1]		
	(ii)	exponent				
			[1]		
(d)	A stu	udent enters the following code into an interpreter.				
		X = 0.1 Y = 0.2 Z = 0.3 OUTPUT $(X + Y + Z)$				
	The	student is surprised to see the output:				
		0.600000000000001				
	Expl	ain why this is output.				

3

A lo	cal c	ollege h	as CSMA/CD in operation	on on its Local Area Network (LAN	l).
(a)	One	e function	n of CSMA/CD is to mor	nitor traffic on the network.	
	Sta	te two of	ther tasks performed by	CSMA/CD.	
	1				
	2				
					[2]
(b)	The	network	uses the TCP/IP protoc	col to transfer files across the netv	vork.
	(i)	State th	nree functions of the TC	P part of this protocol.	
		1			
		2			
					[3]
	(ii)	State tv	vo functions of the IP pa	art of this protocol.	
		1			
					[2]
	(iii)	Identify network		ocol that could be used to transfer	files across the college
					[1]
(c)			re essential for succes e operates on many lay	sful transmission of data over a	
	Giv	e an app	ropriate protocol for eac	ch layer in the table.	
			Layer	Protocol	
			Application		
			Transport		_
			·		
			Internet		

The TCP/IP protocol is used to send an email message from one node on a LAN to a node on a different LAN.
State the steps that take place when the email message is sent and received.
[4]

4 (a) A Boolean expression corresponds to the following truth table.

	INPUT		OUTPUT
Α	В	С	Х
0	0	0	0
0	0	1	0
0	1	0	0
0	1	1	1
1	0	0	0
1	0	1	1
1	1	0	1
1	1	1	1

(-)	(i)	Write the Boolean	expression for	the truth	table by	applying the	sum-of-produc	ts
-----	-----	-------------------	----------------	-----------	----------	--------------	---------------	----

(ii) Complete the Karnaugh Map (K-map) for the truth table.

AB

		00	01	11	10
С	0				
	1				

[1]

(iii) The K-map can be used to simplify the expression in part (a)(i).

Draw loop(s) around appropriate groups of 1s in the table in **part (a)(ii)** to produce an optimal sum-of-products. [3]


(iv) Write the simplified sum-of-products expression for your answer to part (a)(iii).

X =[3]

(b) A logic circuit with four inputs produces the following truth table.

	INF	TUT		OUTPUT
Α	В	С	D	X
0	0	0	0	0
0	0	0	1	0
0	0	1	0	0
0	0	1	1	0
0	1	0	0	1
0	1	0	1	0
0	1	1	0	0
0	1	1	1	0
1	0	0	0	0
1	0	0	1	0
1	0	1	0	0
1	0	1	1	0
1	1	0	0	1
1	1	0	1	1
1	1	1	0	1
1	1	1	1	1

(i) Complete the K-map that corresponds to the truth table.



[4]

(ii) Draw loop(s) around appropriate groups of 1s in the table in **part** (b)(i) to produce an optimal sum-of-products. [2]

(iii) Write the simplified sum-of-products expression for your answer to part (b)(ii).

X =[2]

A computer process can be in one of three states: running, ready or blocked.

5

(a)	Exp	lain how the processes are affected when the following events take place.
	(i)	The running process needs to read a file from a disk.
		[2]
	(ii)	The running process uses up its time slice.
		[2]
(b)	(i)	State the conditions that are necessary for a process to move from the ready to the running state.
		[2]
	(ii)	State the conditions that are necessary for a process to move from the blocked to the ready state.
		[2]

(c) Give three reasons why process scheduling is needed.

1	
2	
3	
	 [3]

6 The compilation process has a number of stages. The first stage is lexical analysis.

A compiler uses a keyword table and a symbol table. Part of the keyword table is shown.

- Tokens for keywords are shown in hexadecimal.
- All of the keyword tokens are in the range 00 5F.

Keyword	Token
←	01
*	02
=	03
ر	ر
IF	4 A
THEN	4B
ENDIF	4C
ELSE	4 D
FOR	4E
STEP	4 F
TO	50
INPUT	51
OUTPUT	52
ENDFOR	53

Entries in the symbol table are allocated tokens. These values start from 60 (hexadecimal). Study the following code.

```
Start ← 1
INPUT Number
// Output values in a loop
FOR Counter ← Start TO 12
    OUTPUT Number * Counter
ENDFOR
```

(a) Complete the symbol table to show its contents after the lexical analysis stage.

Symbol	Token					
Symbol	Value	Туре				
Start	60	Variable				
1	61	Constant				

					l				l							[3]
(b)		output to			al an	alysis	stage	is sto	red in	the fo	llowing	g table	e. Eacl	h cell	stores	one
		nplete th art (a) .	ne outp	out froi	m the	lexica	l anal	ysis s	tage.	Use th	e key	word 1	able a	and yo	our ans	swer
60	0	1														
																[2]
(c)	The	output	of the I	exical	analy	sis sta	age is	the in	put to	the sy	/ntax	analys	sis sta	ge.		
	lder	ntify two	tasks	in syn	tax ar	nalysis	S.									
	1															
	2															
																[2]
(d)	The	final sta	age of	compi	lation	is opti	imisat	ion.								
	(i)	Code o	ptimis	ation p	roduc	ces co	de tha	t mini	mises	the a	moun	t of me	emory	used		
	Give one additional reason why code optimisation is performed.															
																F41

(ii) A student uses the compiler to compile some different code.

After the syntax analysis stage is complete, the compiler generates object code.

The following lines of code are compiled.

```
X \leftarrow A + B

Y \leftarrow A + B + C

Z \leftarrow A + B + C + D
```

The compilation produces the following assembly language code.

LDD 236	//	loads value A to accumulator
ADD 237	//	adds value B to accumulator
STO 512	//	stores accumulator in X
LDD 236	//	loads value A to accumulator
ADD 237	//	adds value B to accumulator
ADD 238	//	adds value C to accumulator
STO 513	//	stores accumulator in Y
LDD 236	//	loads value A to accumulator
ADD 237	//	adds value B to accumulator
ADD 238	//	adds value C to accumulator
ADD 239	//	adds value D to accumulator
STO 514	/ /	stores accumulator in Z

Rewrite the assembly language code after it has been optimised.

BLANK PAGE

BLANK PAGE

Permission to reproduce items where third-party owned material protected by copyright is included has been sought and cleared where possible. Every reasonable effort has been made by the publisher (UCLES) to trace copyright holders, but if any items requiring clearance have unwittingly been included, the publisher will be pleased to make amends at the earliest possible opportunity.

To avoid the issue of disclosure of answer-related information to candidates, all copyright acknowledgements are reproduced online in the Cambridge International Examinations Copyright Acknowledgements Booklet. This is produced for each series of examinations and is freely available to download at www.cie.org.uk after the live examination series.

Cambridge International Examinations is part of the Cambridge Assessment Group. Cambridge Assessment is the brand name of University of Cambridge Local Examinations Syndicate (UCLES), which is itself a department of the University of Cambridge.